"CP1" 120/208V., 1Ø, 3W., S.N., 100A. M.L.O. — UPSTREAM DEVICE - 40A

LOAD TYPE (LABEL)	LOAD (KVA) B	C	CODE	BREAKER SIZE	WIRE SIZE	CIRCUIT NUMBER	CIRCUIT NUMBER	WIRE SIZE	BREAKER SIZE	CODE	LOAD (KVA) B	C	LOAD TYPE (LABEL)
SALES DESK	0.2		X	20	10	1	2	8	20	X	0.2		SALES DESK
SALES DESK		0.2	X	20	10	3	4	10	20	X		0.2	SALES DESK
SALES DESK	0.2		X	20	10	5	6	8	20	X	0.2		SALES DESK
SECURITY SYSTEM	8			20		7			20			0.0	SPARE
FIRE ALARM SYSTEM	0.5		X	20	12	9	10		20		0.0		SPARE
RECEIVING OFFICE		0.7	X	20	10	11	12		20			0.0	SPARE
BMS/GEN-SET ELECT.	0.3		P	15	-	13	14	6	20	X	0.2		IDF #3
IDF #2		0.2	X	20	10	15	16			X		0.2	
	0.2		X			17	18				0.0		SPACE ONLY
SPARE		0.0		20		19	20					0.0	SPACE ONLY
SHUNT TRIP	0.1		X	20	12	21	22				0.0		SPACE ONLY
DIMMING PANEL/BACNET		0.5	X	20	12	23	24					0.0	SPACE ONLY
SPACE ONLY	0.0					25	26				0.0		SPACE ONLY
SPACE ONLY		0.0				27	28					0.0	SPACE ONLY
SPACE ONLY	0.0					29	30	14	15	P	0.1		CONVENIENCE OUTLET

TOTAL CONN. LOAD 4.7 KVA 22.6 AMPERES — PHASE B 2.2 KVA
PANEL DE-RATING 80% 28.3 AMPERES — PHASE C 2.5 KVA

"CP2" 120/208V., 1Ø, 3W., S.N., 125A. M.C.B. — UPSTREAM DEVICE - 125A

LOAD TYPE (LABEL)	LOAD (KVA) B	C	CODE	BREAKER SIZE	WIRE SIZE	CIRCUIT NUMBER	CIRCUIT NUMBER	WIRE SIZE	BREAKER SIZE	CODE	LOAD (KVA) B	C	LOAD TYPE (LABEL)
SALES DESK	0.2		X	20	10	1	2	8	20	X	0.2		GC SALES
SALES DESK		0.2	X	20	10	3	4	8	20	X		0.2	GC SALES
SALES DESK	0.2		X	20	10	5	6	8	20	X	0.2		GC SALES
SALES DESK		0.2	X	20	10	7	8	8	20	X		0.2	GC SALES
SALES DESK	0.2		X	20	10	9	10	10	20	X	0.2		SALES DESKS
SALES DESK		0.2	X	20	10	11	12	10	20	X		0.2	SALES DESKS
SALES DESK	0.2		X	20	10	13	14	12	20	X	0.4		MONEY ROOM
RETURNS, PROD. PICK-UP		1.2	X	20	10	15	16	12	20	X		0.2	COMPUTER OUTLET
AP OFFICE	0.4		X	20	10	17	18	12	20	X	0.2		COMPUTER OUTLET
OFFICES		0.7	X	20	10	19	20	12	20	X		0.2	SECURITY SYSTEM
SPARE	0.0			20		21	22		20		0.0		SPARE
BMS ELECTRONICS		0.2	P	15	14	23	24	12	20	X		0.2	FIRE ALARM PANELS
IDF #1	0.2		X	20	8	25	26	12	20	X	0.5		LOWES UNIVERSITY
	0.2		X			27	28	2	40	X		2.5	
TRAINING ROOM	0.9		X	20	10	29	30			X	2.2		PANEL - CP1
SALES DESK		0.2	X	20	10	31	32	12	20	X		0.2	FIRE ALARM PANELS
SALES DESK	0.2		X	20	10	33	34	10	20	X	0.2		SALES DESKS - SCO
SALES DESK		0.2	X	20	10	35	36	12	20	X		0.2	TELE/DATA EQUIPMENT
SALES DESK	0.2		X	20	10	37	38	12	20	X	0.2		TELE/DATA EQUIPMENT
TELE/DATA EQUIPMENT		0.6	X	20	12	39	40	8	20	X		0.2	IDF #4
TELE/DATA OUTLET - 208V	0.2		X	30	10	41	42			X	0.2		
	0.2		X			43	44	10	20	X		0.2	SALES DESKS
BDA EQUIPMENT	0.4		*	20	12	45	46	10	20	X	0.2		CASH RECYCLER
SPACE ONLY		0.0				47	48					0.0	SPACE ONLY
SPACE ONLY	0.0					49	50				0.0		SPACE ONLY
SPACE ONLY		0.0				51	52					0.0	SPACE ONLY
SPACE ONLY	0.0					53	54				0.0		SPACE ONLY

TOTAL CONN. LOAD 16.6 KVA 79.8 AMPERES (3) — PHASE B 8.0 KVA (3)
PANEL DE-RATING 80% 99.8 AMPERES — PHASE C 8.6 KVA

"MG-FP" 277/480V., 3Ø, 4W., S.N., 300 AMPERE, LINE/LOAD CB, S.E. RATED, NEMA 3R — UPSTREAM DEVICE - GENERATOR

LOAD TYPE (LABEL)	LOAD (KVA) A	B	C	CODE	BREAKER SIZE	WIRE SIZE	CIRCUIT NUMBER
FIRE PUMP (100 HP)	34.4	34.4	34.4	X	300	#4/0 CU #2/0 AL	1

TOTAL CONN. LOAD 103.2 KVA 124.1 AMPERES — PHASE A 34.4 KVA; PHASE B 34.4 KVA; PHASE C 34.4 KVA

"MDPA" 277/480V., 3Ø, 4W., S.N., 1600 AMPERE SWITCHBOARD - M.L.O. — UPSTREAM DEVICE - 1600A

LOAD TYPE (LABEL)	LOAD (KVA) A B C	CODE	BREAKER SIZE	WIRE SIZE	CIRCUIT NUMBER
PANEL - MDPB (100% FULLY RATED BREAKER)	148.3 / 158.7 / 152.4	X	600	2#600 CU 2#600 AL	1
PANEL - HVAC1	114.2 / 114.2 / 98.1	X	600	2#600 CU 2#600 AL	2
PANEL - HVAC2	120.6 / 120.6 / 120.6	X	600	2#600 CU 2#600 AL	3
PANEL - ELS	5.0 / 3.8 / 3.6	X	70	#4 CU #1 AL	4
SPACE ONLY	0.0 / 0.0 / 0.0				5
SPACE ONLY	0.0 / 0.0 / 0.0				6
SPACE ONLY	0.0 / 0.0 / 0.0				7
TVSS FACTORY INSTALLED	0.0 / 0.0 / 0.0	P	60	-	8

TOTAL CONN. LOAD 1160.1 KVA 1395.4 AMPERES (3) — PHASE A 388.1 KVA; PHASE B 397.3 KVA (3); PHASE C 374.7 KVA

"MDPB" 277/480V., 3Ø, 4W., S.N., 600 AMPERE SWITCHBOARD - M.L.O. — UPSTREAM DEVICE - 600A

LOAD TYPE (LABEL)	LOAD (KVA) A B C	CODE	BREAKER SIZE	WIRE SIZE	CIRCUIT NUMBER
PANEL - LP1	14.0 / 11.6 / 13.6	X	225	#3/0 CU #3/0 AL	1
PANEL - LP2	14.3 / 12.9 / 13.4	X	225	#3/0 CU #3/0 AL	2
PANEL - LP3	6.5 / 7.2 / 5.4	X	125	#1/0 CU #1/0 AL	3
PANEL - BC	33.1 / 33.1 / 33.1	X	225	#3/0 CU #3/0 AL	4
PANEL - BW - XFMR	40.5 / 41.5 / 42.0	X	225	#3/0 CU #3/0 AL	5
PANEL - RP1 - XFMR	11.1 / 15.2 / 12.1	X	125	#1/0 CU #1/0 AL	6
PANEL - RP2 - XFMR	28.8 / 37.2 / 32.8	X	225	#3/0 CU #3/0 AL	7
TVSS FACTORY INSTALLED	0.0 / 0.0 / 0.0	P	30	-	8

TOTAL CONN. LOAD 459.4 KVA 552.6 AMPERES (3) — PHASE A 148.3 KVA; PHASE B 158.7 KVA (3); PHASE C 152.4 KVA

"BW" 120/208V., 3Ø, 4W., S.N., 500A. M.C.B. — UPSTREAM DEVICE - N/A

LOAD TYPE (LABEL)	LOAD (KVA) A	B	C	CODE	BREAKER SIZE	WIRE SIZE	CIRCUIT NUMBER	CIRCUIT NUMBER	WIRE SIZE	BREAKER SIZE	CODE	LOAD (KVA) A	B	C	LOAD TYPE (LABEL)
BUSWAY - 1	4.5			E+	100	3	1	2	#1/0	100	E+	4.5			BUSWAY - 2
SALES		4.5		E+			3	4			E+		4.5		SALES
			4.5	E+			5	6			E+			4.5	
BUSWAY - 3	4.5			E+	100	#1/0	7	8		100	E+	4.5			BUSWAY - 4
SALES		4.5		E+			9	10	2		E+		4.5		SALES
			4.5	E+			11	12			E+			4.5	
BUSWAY - 5	4.5			E+	100	#2/0	13	14		100	X	4.5			BUSWAY - 6
SALES		4.5		E+			15	16	#1/0		X		4.5		SALES
			4.5	E+			17	18			X			4.5	
BUSWAY - 7	4.5			X	100	#1/0	19	20		100	E+	4.5			BUSWAY - 8
SALES		4.5		X			21	22	#2/0		E+		4.5		SALES
			4.5	X			23	24			E+			4.5	
BUSWAY - 9	4.5			X	100	3	25	26			0.0				SPACE ONLY
SALES		4.5		X			27	28				0.0			SPACE ONLY
			4.5	X			29	30					0.0		SPACE ONLY
SPACE ONLY	0.0						31	32			0.0				SPACE ONLY
SPACE ONLY		0.0					33	34				0.0			SPACE ONLY
SPACE ONLY			0.0				35	36					0.0		SPACE ONLY
SPACE ONLY	0.0						37	38			0.0				SPACE ONLY
SPACE ONLY		0.0					39	40	—	15	P	1.0			BMS RELAY CNTRL (BUSWAY)
SPACE ONLY			0.0				41	42	—	15	P			1.5	BMS RELAY CONTROLS

TOTAL CONN. LOAD 124.0 KVA 344.2 AMPERES — PHASE A 40.5 KVA
PANEL DE-RATING 80% 430.3 AMPERES — PHASE B 41.5 KVA; PHASE C 42.0 KVA

"MGP" 277/480V., 3Ø, 4W., S.N., 600 AMPERE LINE/LOAD CB, S.E. RATED, NEMA 3R — UPSTREAM DEVICE - GENERATOR

LOAD TYPE (LABEL)	LOAD (KVA) A	B	C	CODE	BREAKER SIZE	WIRE SIZE	CIRCUIT NUMBER
PANEL - MDPB (SHUNT-TRIP)	121.3	131.7	125.4	ST	600	2#600 CU 2#600 AL	1

TOTAL CONN. LOAD 378.4 KVA 455.1 AMPERES (3) — PHASE A 121.3 KVA; PHASE B 131.7 KVA (3); PHASE C 125.4 KVA

"MGE" 277/480V., 3Ø, 4W., S.N., 70 AMPERE LINE/LOAD CB, S.E. RATED, NEMA 3R — UPSTREAM DEVICE - GENERATOR

LOAD TYPE (LABEL)	LOAD (KVA) A	B	C	CODE	BREAKER SIZE	WIRE SIZE	CIRCUIT NUMBER
PANEL - ELS	5.0	3.8	3.6	X	70	#4 CU #1 AL	1

TOTAL CONN. LOAD 12.4 KVA 14.9 AMPERES — PHASE A 5.0 KVA; PHASE B 3.8 KVA; PHASE C 3.6 KVA

LOAD SUMMARY

AIR CONDITIONING	695.5 KVA
INTERIOR LIGHITNG	49.1 KVA (3)
EXTERIOR LIGHTING & SIGNS	12.6 KVA
EMERGENCY LIGHTING	10.9 KVA
WATER HEATING	4.0 KVA
GENERAL POWER & MISC.	191.8 KVA (3)
SALES FLOOR DISPLAYS	121.5 KVA
BATTERY CHARGERS	74.7 KVA (3)
-	0.0 KVA
TOTAL CONNECTED LOAD (KVA)	1160.1 KVA (3)
TOTAL CONNECTED LOAD (AMP)	1395.4 AMP

NOTE:
SWITCHGEAR PROVIDER SHALL PROVIDE IN THEIR "OWNER FURNISHED" PRICING TO LOWE'S, A PER PROJECT SYSTEM START UP PROCESS FOR EACH NEW SWITCHGEAR ORDER. A FACTORY AUTHORIZED SERVICE REPRESENTATIVE SHALL VERIFY AND/OR PERFORM THIS ON-SITE EQUIPMENT START UP PROCEDURE PRIOR TO THE COMMENCEMENT OF THE BUILDING COMMISSIONING. PM8000 METER OR EQUIVALENT SHALL BE SET UP TO PROPERLY COMMUNICATE WITH LOWE'S BMS SYSTEM. DURING BUILDING COMMISSIONING, ANY DEFICIENCIES OR CONNECTION ISSUES FOUND DUE TO THE METER NOT PROGRAMMED OR INCORRECTLY PROGRAMMED, SHALL BE THE RESPONSIBILITY OF THE PROVIDER TO CORRECT AT NO ADDITIONAL EXPENSE TO LOWE'S. (3)

- START UP/INITIAL TESTING, IP ADDRESS PROGRAMMING (**IP ADDRESS 10.21.9.196**), AND COMMUNICATION MODE PROGRAMMING

SWITCHGEAR NOTES

1. THE ELECTRICAL SUBCONTRACTOR EXCEPT AS OTHERWISE NOTED SHALL PROVIDE ALL WIRING CONDUIT, FITTINGS, DISCONNECTS AND ELECTRICAL EQUIPMENT BEYOND SWITCHGEAR CABINETS.
2. ALL "SWITCHGEAR CENTERS" AS SHOWN ON THE DRAWINGS SHALL BE FURNISHED BY THE OWNER. EACH "SWITCHGEAR CENTER" IS PREFABRICATED FOR LOWE'S COMPANIES, INC. AND SHALL INCLUDE THE FOLLOWING:
   - 2.1. ALL OVER CURRENT DEVICES, LIGHTING CONTACTORS, BUILDING MANAGEMENT CONTROL SYSTEM AND OTHER MISCELLANEOUS COMPONENTS.
   - 2.2. 480VAC TO 120/208VAC STEP-DOWN TRANSFORMERS
   - 2.3. MAIN SERVICE DISCONNECTS AND/OR SWITCHBOARDS
   - 2.4. UTILITY PULL AND METERING SECTIONS AS REQUIRED.
   - 2.5. PRE-PROGRAMMED POWERLINK CONTROLLER - SEE PANEL SCHEDULES & CONTROL SCHEDULE NOTES

   EACH "SWITCHGEAR CENTER" IS U.L. 891 LISTED AS A "DEAD FRONT SWITCHBOARD".
3. THERE ARE CURRENT TRANSFORMERS (CT'S) LOCATED IN THE MAIN BREAKER SECTION. THESE CURRENT TRANSFORMERS (CT'S) ARE STRICTLY FOR THE OPERATION OF THE BUILDING MANAGEMENT SYSTEM ONLY. UTILITY COMPANY CT'S, IF REQUIRED, MUST BE MOUNTED IN A SEPARATE ENCLOSURE.
4. IF A SEPARATE CT CABINET, PULL SECTION OR MAIN DISCONNECT IS REQUIRED BY THE LOCAL POWER COMPANY FOR THEIR METERING EQUIPMENT, IT SHALL BE FURNISHED AND INSTALLED BY THE ELECTRICAL SUBCONTRACTOR, UNLESS CALLED FOR ON THESE PLANS TO BE FURNISHED WITH OWNER'S EQUIPMENT. COORDINATION WITH THE LOCAL POWER COMPANY TO PROVIDE ALL REQUIRED METERING EQUIPMENT WILL BE THE RESPONSIBILITY OF THE ELECTRICAL SUBCONTRACTOR. IF THIS ADDITIONAL EQUIPMENT IS PROVIDED BY THE ELECTRICAL SUBCONTRACTOR, IT MUST BE COORDINATED WITH THE SWITCHGEAR MANUFACTURER TO ENSURE U.L. LISTING INTEGRITY.
5. INSTALLATION OF THE "SWITCHGEAR CENTERS" SHALL BE THE RESPONSIBILITY OF THE ELECTRICAL SUBCONTRACTOR. THE "SWITCHGEAR CENTERS" CONSIST OF FREESTANDING ENCLOSURE SECTIONS THAT BOLT TOGETHER WITH HARDWARE PROVIDED. THE CABINETS HAVE "OPEN BOTTOMS" TO FACILITATE CONDUIT ROUGH-IN AND INSTALLATION. THE MANUFACTURER SHOULD BE CONTACTED FOR CABINET DETAILS PRIOR TO ROUGHING IN ANY UNDERGROUND CONDUIT.
6. THE ELECTRICAL SUBCONTRACTOR WILL MAKE ALL NECESSARY KNOCKOUTS IN THE TOP OF THE CABINETS AS REQUIRED TO INSTALL ALL OVERHEAD CONDUITS. ELECTRICAL SUBCONTRACTOR SHALL USE EXTREME CAUTION AS TO PREVENT METAL CHIPS, SAWDUST, FILINGS, ETC. FROM ENTERING CABINETS.
7. WHERE POSSIBLE, SOME OF THE FEEDER CONDUCTORS FOR THE INTERCONNECTION BETWEEN SOME CABINET SECTIONS ARE PROVIDED AS SHOWN ON SHEETS E9.00 AND E9.01.
8. ALL REQUIRED CONTROL WIRING BETWEEN INTERCONNECTED CABINET SECTIONS IS FACTORY INSTALLED. CONNECTION METHOD BETWEEN CABINET SECTIONS SHALL BE VIA FACTORY INSTALLED POLARIZED PLUG ASSEMBLIES. ELECTRICAL SUBCONTRACTOR SHALL CONNECT THESE POLARIZED PLUG ASSEMBLIES TOGETHER ONCE THE CABINET SECTIONS ARE SET IN PLACE.
9. TERMINAL STRIPS ARE PROVIDED IN THE TOP SECTIONS OF ALL CABINETS WITH ENERGY MANAGEMENT SYSTEM CONTROLS. THE TERMINAL STRIPS ARE LABELED WITH NUMBERS CORRESPONDING TO THE CIRCUIT NUMBERS ON THE PANEL BOARD SCHEDULES. ALL CIRCUITS WITH AN "E" OR "T" IN THE CODE COLUMN ON THE PANEL BOARD SCHEDULE WILL BE CONNECTED TO THIS TERMINAL STRIP. WIRE SIZES SHOWN ON THE PANEL BOARD SCHEDULES REFER TO WIRE SIZE FROM THIS TERMINAL STRIP AND SHALL BE MAINTAINED THROUGHOUT THE ENTIRE LENGTH OF THE CIRCUIT.
10. THE ELECTRICAL SUBCONTRACTOR WILL WIRE CIRCUITS THAT ARE SHOWN WITH AN "X" IN THE CODE COLUMN ON THE PANEL BOARD SCHEDULES DIRECTLY TO THE RESPECTIVE CIRCUIT BREAKER. NO TERMINAL STRIPS ARE PROVIDED FOR THESE CIRCUITS.
11. AFTER INSTALLATION OF THE SWITCHGEAR CABINETS ARE COMPLETE AND THE CHECKOUT AND STARTUP PROCEDURES AREA COMPLETED, IT IS THE RESPONSIBILITY OF THE ELECTRICAL SUBCONTRACTOR TO ENSURE THAT ALL CABINET COVERS AND DOORS ARE IN PLACE AND SECURED PROPERLY. ELECTRICAL SUBCONTRACTOR SHALL VACUUM THE INTERIOR OF ALL CABINETS TO REMOVE ALL DEBRIS.
12. ALL CIRCUIT BREAKERS FOR LED LIGHTING CIRCUITS SHALL BE TYPE "SWD" BREAKERS MANUFACTURED SPECIFICALLY FOR THAT PURPOSE.
13. ALL U.L. LISTED CIRCUIT BREAKERS RATED 125 AMPERES OR LESS SHALL BE MARKED AS BEING SUITABLE FOR 75°C ONLY OR 60/75° CONDUCTOR.
14. SWITCHGEAR SHALL BE FULLY OR SERIES RATED AS INDICATED ON SHEET E9.00 AT 65,000 AIC. ELECTRICAL SUBCONTRACTOR SHALL BE RESPONSIBLE FOR VERIFYING AIC WITH LOCAL ELECTRIC UTILITY BASED ON SELECTED TRANSFORMER SIZE.

PANEL & DIMMING CONTROL SCHEDULE CODES

X - NOT CONTROLLED BY BUILDING MANAGEMENT SYSTEM

E - CONTROLLED BY BUILDING MANAGEMENT SYSTEM VIA RELAYS/CONTACTORS.

E+ - CONTROLLED BY ENERGY MANAGEMENT SYSTEM - NOT GENERATOR BACKED UP.

D - CONTROLLED BY ENERGY MANAGEMENT SYSTEM & "DAYLIGHTING" PHOTOCELLS. (SEE SHEET E-2.03)

P - PRE-WIRED IN SWITCHGEAR CABINETS.

ST - SHUNT TRIP BREAKER

G - GFCI TYPE BREAKER

* - PROVIDE BREAKER HANDLE LOCK

ELECTRICAL ROOMS #1 & #2 - PANELS LP1, LP2, & LP3

E1 - SITE SECURITY LIGHTING (STAGE 1) CONTROLLED BY BUILDING MANAGEMENT SYSTEM AND GARDEN CENTER PHOTOCELL. ON/OFF TIME SCHEDULE CONTROL MANAGED BY BUILDING MANAGEMENT SYSTEM. POWERLINK INPUT #1

E2 - SITE LIGHTING (STAGE 2) CONTROLLED BY BUILDING MANAGEMENT SYSTEM AND GARDEN CENTER PHOTOCELL. ON/OFF TIME SCHEDULE CONTROL MANAGED BY BUILDING MANAGEMENT SYSTEM. POWERLINK INPUT #2

E3 - SITE LIGHTING (STAGE 3) CONTROLLED BY BUILDING MANAGEMENT SYSTEM AND GARDEN CENTER PHOTOCELL. ON/OFF TIME SCHEDULE CONTROL MANAGED BY BUILDING MANAGEMENT SYSTEM. POWERLINK INPUT #3

E4 - BUILDING SIGNS CONTROLLED BY BUILDING MANAGEMENT SYSTEM AND GARDEN CENTER PHOTOCELL. ON/OFF TIME SCHEDULE CONTROL MANAGED BY BUILDING MANAGEMENT SYSTEM. POWERLINK INPUT #4

E5 - SITE SIGNS CONTROLLED BY BUILDING MANAGEMENT SYSTEM AND GARDEN CENTER PHOTOCELL. ON/OFF TIME SCHEDULE CONTROL MANAGED BY BUILDING MANAGEMENT SYSTEM. POWERLINK INPUT #5

ELECTRICAL ROOM #1 - PANELS LP1 & LP2

E6 - SALES FLOOR LIGHTING (50%) CONTROLLED BY BUILDING MANAGEMENT SYSTEM AND DIMMING PANEL. 50% LIGHT LEVEL IN EMPLOYEE MODE. 100% LIGHT LEVEL IN OCCUPIED MODE. OFF IN UNOCCUPIED MODE. ON/OFF TIME SCHEDULE CONTROL MANAGED BY BUILDING MANAGEMENT SYSTEM AND IN CONJUNCTION WITH UNARMING/ARMING OF SECURITY SYSTEM. POWERLINK INPUT #6

E7 - GARDEN CENTER CANOPY LIGHTING CONTROLLED BY BUILDING MANAGEMENT SYSTEM AND GARDEN CENTER PHOTOCELL. ON/OFF TIME SCHEDULE CONTROL MANAGED BY BUILDING MANAGEMENT SYSTEM. POWERLINK INPUT #7

E8 - GARDEN CENTER SHADE STRUCTURE LIGHTING CONTROLLED BY BUILDING MANAGEMENT SYSTEM AND GARDEN CENTER PHOTOCELL. ON/OFF TIME SCHEDULE CONTROL MANAGED BY BUILDING MANAGEMENT SYSTEM. POWERLINK INPUT #8

ELECTRICAL ROOM #2 - PANEL LP3

E6 - VESTIBULE LIGHTING CONTROLLED BY BUILDING MANAGEMENT SYSTEM. ON/OFF TIME SCHEDULE CONTROL MANAGED BY BUILDING MANAGEMENT SYSTEM. POWERLINK INPUT #6

E7 - LUMBER/CANOPY LIGHTING CONTROLLED BY BUILDING MANAGEMENT. ON/OFF TIME SCHEDULE CONTROL MANAGED BY BUILDING MANAGEMENT SYSTEM.. POWERLINK INPUT #7

E8 - SPARE
POWERLINK INPUT #8

FINAL	SECOND	ORIGINAL

REVISIONS
◇ PRE-BID SET ISSUE DATE △ POST BID SET ISSUE DATE

DATE		DESCRIPTION
10.10.2025	1	PLAN REVIEW COMMENTS
10.31.2025	2	CITY REVIEW COMMENTS
10.07.2026	3	CRITERIA UPDATES

Carl Page — Digitally signed by Carl Page — Date: 2026.10.07 14:27:19-05'00'
No. 0050265 STATE OF FLORIDA PROFESSIONAL ENGINEER
10.07.2026

PAGE INTERWORKS, P.A. ENGINEERS & CONSULTANTS
7523 MAIN STREET, NORTH WILKESBORO, NC 28659
PHONE: 336-667-4225
LICENSE: NCARB - 44575 NEW JERSEY Lic. No. 12114 NEW YORK Lic. No. 024875-1 FLORIDA Lic. No. 0401 01655 VIRGINIA Lic. No. RA-0105010-B FLORIDA Lic. No. AR95156

PERRY M. PETRILLO ARCHITECTS PC
9 Park Avenue
Park Ridge, New Jersey 07656
Telephone (201) 307-6153
Facsimile (201) 307-6158

LOWE'S HOME CENTERS, LLC
1000 LOWE'S BOULEVARD
MOORESVILLE, NC 28117
704.758.1000 (PH.)

THIS DRAWING IS THE PROPERTY OF LOWE'S HOME CENTERS, LLC. ANY USE OR REPRODUCTION IN WHOLE OR PART IS PROHIBITED WITHOUT THE EXPRESSED WRITTEN CONSENT OF LOWE'S HOME CENTERS, LLC. ©COPYRIGHT 2025-2027 ALL RIGHTS RESERVED.

LOWE'S

PANELBOARD SCHEDULES

LOWE'S OF WESTLAKE
5683 SEMINOLE PRATT WHITNEY RD.
Westlake, Florida, 33470

PCN: 77-49-43.01-28-000.0010
PROJECT No: 24209 | DRAWN BY: JBM | CHECKED BY: CWP

CRITERIA
ISSUE DATE: 02-2025
PERMIT SET
ISSUE DATE: 08-22-2025
CONSTRUCTION SET
ISSUE DATE: 04-14-2025
DRAWING NUMBER:
E10.01